



**PRE-WIRED KIT**

The Pre-Wired Kit is provided for the connection through the TSA4 Telealarm device, placed on the cabin roof, and the alarm plate, placed into the cabin.

The kit includes:

- n° 1 pre-wired cable UniCo TSA4 / Plate, 3 meters long;
- n° 4 telephone sockets;
- n° 2 plug/plug telephone cables 30 centimeters long (1 to be connected as in the scheme and 1 in addition);
- n° 1 telephone cable plug/terminal in addition

Bridge TSA	TSA	Functions	Pre-Wired Cable	Button and lights	Handsfree
	J8	1 (-) Negative Handsfree power supply	<b>Grey</b>		1
		2 Handsfree's Loudspeaker	<b>Blue</b>		3
		3 Handsfree's Microphone	<b>White</b>		2
		4 Alarm Input	<b>Brown</b>	N.O.	
		5 Relay 1			
		6 Relay 1	<b>Yellow</b>	+G	
		7 Relay 2			
		8 Relay 2	<b>Green</b>	+V	
J5	A (+) Positive Power Supply 12/16 Vdc				
	B (-) Negative Power Supply 12/16 Vdc				
J6	1 Telephone of Service for Maintainer's Alarm				
	2 Telephone of Service for Maintainer's Alarm				
	3 (+) Positive Handsfree Power Supply	<b>Red</b>		4	
	4 Technological Alarm / Gong or Filter				
	5				
	6	Eventual Intercom Handset			
	7				
	8 Handset's Ground	<b>Pink</b>	CM/(-) <sup>(*)</sup>		

(\*) The CM and (-) contact of the button must be connected in parallel